

Netzwerkinstallation auf dem Server

SWAP (E:)

ffServer2

FF-Server Verzeichnis keine Freigabe keine Arbeitsplatzfreigabe

E:\ffServer2

Dateiname

- dbn\_01
- Programme
- dir.txt
- Dupdate.exe
- FFALIAS.SC\$
- ffcomms.exe
- ffe.cnt
- ffe.exe
- FFE.GID
- ffe.hlp
- FFE.INI
- FFSALIAS.FF2
- ffserver.cnt
- ffserver.exe
- FFServer.GID
- ffserver.hlp
- FFServer.ini
- FFSINFO.FF2

Datenverzeichnis keine Arbeitsplatzfreigabe

Anwendungs -Programmverzeichnis für die Arbeitplätze muss auf dem Server freigegeben werden

Datenbank-Update-Programm

Vorgabe-Einstellungsdatei für Datenverzeichnisse für die Erstinstallation

Datenbank - Server Programm muss aktiviert sein damit die Arbeitplätze Daten abrufen dürfen

E:\ffServer2\Programme\buerod

Anwendungsverzeichnis für die Arbeitplätze -> Netzwerkfreigabe erforderlich

Dateiname

- 01Deutsch.adm
- buerod.cnt
- buerod.exe
- BUEROD.HLP
- ffcomms.exe

Deutsches Wörterbuch

Anwendungsdatei für den Arbeitsplatz

Hilfe-Datei

Arbeitsplatz - Protokoll - Einstellung

FF-Server Standard-Einstellungen

**TurboPower FlashFiler [GallData]**

Server Config Debug Help

Name	State	Clients	Sessions	Open Databases	Open Tables	Cursors	RAM (MB)
GallData	Started	0	0	0	0	0	0

  

Name	Address	State	Clients	Messages	Messages/Sec
IPX/SPX (FF)		Driver not installed	0	0	0.0000
Single User (FF)	Local	Started	0	0	0.0000
TCP/IP (FF)	192.167.115.56	Started	0	0	0.0000

Up: 0:00:00:06

Config Debug Help

- General... Ctrl+G
- Network... Ctrl+N
- User Permissions... Ctrl+U
- Aliases... Ctrl+A
- User-Defined Indexes... Ctrl+X

**FlashFiler Server General Configuration**

General

Server name: GallData

Maximum RAM (in MB): 60

Temporary storage (in MB): 100

Server priority: Highest

Startup Options

- Bring Server up automatically
- Start minimized

Garbage Collection

- Enabled
- Collection frequency (millisec): 300000

Keep Alive Options

Interval from last message: 30000

Interval between Keep Alives: 5000

Keep Alive retries: 5

OK Cancel

Config Debug Help

- General... Ctrl+G
- Network... Ctrl+N
- User Permissions... Ctrl+U
- Aliases... Ctrl+A
- User-Defined Indexes... Ctrl+X

**FlashFiler Network Configuration**

Winsock TCP/IP Transport

- Enabled
- Listen for broadcasts
- TCP port: 25445
- UDP server port: 25445
- UDP client port: 25701
- Network interface: Adapter 0: 192.167.115.56

Winsock IPX/SPX Transport

- Enabled
- Listen for broadcasts
- IPX server socket: 25445
- IPX client socket: 25701
- SFX socket: 25957

Single User Transport

- Enabled

OK Cancel

Config Debug Help

- General... Ctrl+G
- Network... Ctrl+N
- User Permissions... Ctrl+U
- Aliases... Ctrl+A
- User-Defined Indexes... Ctrl+X

**FlashFiler Server Aliases**

Alias	Path
dBuero01	E:\FFServer2\dbN_01

OK Cancel